

SUNRIDGE REPEATER SYSTEM

NOTE: all calls are publicly broadcast – USE DISCRETION.

How to use the AUTOPATCH.

EMERGENCY USE

- Step 1 –In an emergency, break into an ongoing contact and ask the stations to stand by for an Emergency Autopatch. Listen for a clear channel.
- Step 2 –Now hold the transmit button down and press the STAR key on the radio keypad to enable the Autopatch. Release the transmit button. You will now hear a dial tone.
- Step 3 –When the dial tone stops, press the transmit button and dial 911 on the radio keypad then release the button.
- Step 4 –Be patience, you will hear the phone ring.
- Step 5 –When 911 answers they will say “ This is 911 what is your emergency “ Press the transmit button and tell them you are calling on a two way radio and say what you are calling about. Be sure to say (over) at this point then release your button. 911 will probably want more information at this time, press the transmit button again and give the additional information then say (over).
- Step 6 –When the call is done press the transmit button and say this is (so and so) clearing the Autopatch with the transmit button still pressed, push the POUND key on the keypad to to disable the Autopatch then release the transmit button. You should hear some beeps on your radio.
- Step 7 –Press the transmit button one more time and say the repeater is now returned to normal use.

NOTE : The repeater my time out in about 3 minutes or so, STAY TO THE POINT.